

Standard Features

MODEL	MT-C125
Standby Power(60Hz)	110KW/137.5KVA
Prime Power(60Hz)	100KW/125KVA
Engine	Cummins 6BTA5.9-G2
Alternator	STAMFORD UCI274D

- **Engine (CCEC Cummins 6BTA5.9-G2)**
- Radiator 40°Cmax, fans are driven by belt, with safety guard
- 24V charge alternator
- **Alternator (STAMFORD UCI274D),**
- single bearing alternator, Protection Class IP22, insulation class H/H
- Dry Type air filter, fuel filter, oil filter, pre-filter, absorber
- Main line circuit breaker
- Standard control panel
- Two 12V batteries, rack and cable
- Ripple flex exhaust pipe, Exhaust siphon, flange, muffler
- Operation manual



Generator Set Ratings						
Voltage	Frequency	Phase	P.F (COS ϕ)	Standby Amps	Standby Ratings (KW/KVA)	Prime Ratings (KW/KVA)
440/254	60	3	0.8	226	137.5/110	125/100
415/240	60	3	0.8	239	137.5/110	125/100
400/230	60	3	0.8	248.2	137.5/110	125/100
380/220	60	3	0.8	261	137.5/110	125/100

Prime Power (PRP): Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97(eqvISO8528); A1 0% overload capability is available for a period of 1 hour within a 12-hour period of operation.

Standby Power Rating (ESP): The standby power rating is applicable for supplying emergency

Dimension Of Generator Set	
Dimension(L*W*H)/CM For Open Type	226×85×150 CM
Net Weight/KG For Open Type	1500KG
Dimension(L*W*H)/CM For Sound Proof Type	323×117×180 CM
Net Weight/KG For Sound Proof Type	1950 KG
Dimension (L*W*H)/MM For Trailer Type	
Net Weight/KG For Trailer Type	

Specification Of Engine		
Engine	Engine Model	6BTA5.9-G2
	Manufacturer	DCEC Cummins
	Prime Power	120KW/161HP
	Standby Power	132KW/177HP
	Engine Configuration	6Cylinder In Line, 4Stroke
	Gas Feeding Model	Turbocharged
	Bore × Stroke	102 × 120 (MM)
	Displacement	5.9L
	Rated Speed	1800RPM
	Speed Governor	Electronic
	Starter Model	24V DC Start
	Fuel Consumption Standby Power (100% load)	211 g/Kw.h
	Fuel Consumption Prime Power (75% load)	212 g/Kw.h
	Oil Consumption	≤4 g/kw.h
	Cooling System	Water Cool
	Compression Ratio	17.0:1
	Max Back Pressure	10KPA
	Max Intake Restriction	6.35KPA
	Exhaust Temperature	570℃

Specification Of Alternator		
Alternator	Alternator Model	UCI274D
	Manufacturer	STAMFORD company
	Prime Output	100KW/125KVA
	Standby Output	110KW/137.5KVA
	Excitation Model	Brushless, Self-Exciting
	Cooling Method	Air Cooling
	Connection Type	3 Phase and 12 Wires "Star" Connection
	Power Factor	0.8
	Protection Class	IP22
	Insulation Class	H
	Altitude	$\leq 1000\text{m}$
	Voltage Regulation, Steady State	$\leq \pm 1\%$
	Telephone Influence Factor	< 50
	Sudden Voltage Warp (100% Sudden Reduce)	$\leq \pm 1\%$
	Sudden Voltage Warp (Sudden Increase)	$\leq \pm 25\%$
	Voltage Stable Time (100% Sudden Reduce)	$\leq 6\text{S}$
	Voltage Stable Time (Sudden Increase)	$\leq 6\text{S}$
	Frequency Reduce	0-5% adjustable
	Frequency Regulation, Stead State	$\leq 1.5\%$
	Frequency Waving	$\leq 0.8\%$
	Sudden Frequency Warp (100% Sudden Reduce)	$\leq +12\%$
	Sudden Frequency Warp (100% Sudden Increase)	$\leq -10\%$
	Frequency Recovery Time (100% Sudden Reduce)	$\leq 5\text{S}$
	Frequency Recovery Time (Sudden Increase)	$\leq 5\text{S}$
Compliance Stands	GB755, BS5000, VDE0530, NEMAMG1-22, IED34-1, CSA22.2 and AS1359	

Control Panel System



MONICAN CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown 4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

1. Emergency Stop Button 2. Voltmeter and Selector Switch
3. Ammeter and Selector Switch 4. Frequency Meter
5. Hour Running Meter 6. Alart Buzzer



SMARTGEN CONTROL MODEL/ MANUAL OR ATSUSE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

Digital type, all function showed by LED



DEEPSEA CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop
- 6 With Remote Teleport Communication RS 485

Parameters of Operation:

Digital type, all function showed by LED