

Standard Features

MODEL	MT-P1000
Standby Power(60Hz)	880KW/1100KVA
Prime Power(60Hz)	800KW/1000KVA
Engine	PERKINS 4008TAG2
Alternator	STAMFORD LVI634C

- **Engine(PERKINS.UK 4008TAG2)**
- Radiator 40°C max, fans are driven by belt, with safety guard
- 24V charge alternator
- **Alternator(STAMFORD LVI634C),**
- single bearing alternator, Protection Class IP22, insulation class H/H
- Dry Type air filter, fuel filter, oil filter, re-filter, absorber
- Main line circuit breaker
- Standard control panel
- Two 12V batteries, rack and cable
- Ripple flex exhaust pipe, Exhaust siphon, flange, muffler
- Operation manual



Generator Set Ratings						
Voltage	Frequency	Phase	P.F (COS ϕ)	Standby Amps	Standby Ratings (KW/KVA)	Prime Ratings (KW/KVA)
380/220	60	3	0.8	1673	880/1100	800/1000
220/127	60	3	0.8	2885	880/1100	800/1000

Prime Power (PRP): Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97(eqvISO8528); A10% overload capability is available for a period of 1 hour within a 12-hour period of operation.

Standby Power Rating (ESP): The standby power rating is applicable for supplying emergency

Dimension Of Generator Set	
Dimension(L*W*H)/CM For Open Type	500×165×225CM
Net Weight/KG For Open Type	10000KG
Dimension(L*W*H)/CM For Sound Proof Type	20FT
Net Weight/KG For Sound Proof Type	12500KG
Dimension (L*W*H)/MM For Trailer Type	
Net Weight/KG For Trailer Type	

Specification Of Engine		
Engine	Engine Model	4008TAG2
	Manufacturer	PERKINS UK
	Emissions statement	EU2007(EU97/68/EC Stage II)
	Prime Power	838KW/1123HP
	Standby Power	924KW/1238HP
	Engine Configuration	8Cylinder In Line, 4Stroke,Direct Injection
	Gas Feeding Model	Turbocharged Air Air cooled
	Bore × Stroke	160 × 190 (MM)
	Displacement	30.561L
	Rated Speed	1800RPM
	Speed Governor	Electrical
	Starter Model	24V DC Start
	Fuel Consumption Prime Power (100% load)	206L/H
	Totally lubrication system Capacity	165.6L
	Coolant capacity	162L
	Cooling System	Water Cool
	Compression Ratio	13.6:1

Specification Of Alternator		
Alternator	Alternator Model	LV1634C
	Manufacturer	STAMFORD company
	Prime Output	800KW/1000KVA
	Standby Output	880KW/1100KVA
	Excitation Model	Brushless, Self-Exciting
	Cooling Method	Air Cooling
	Connection Type	3 Phase and 12 Wires "Star" Connection
	Power Factor	0.8
	Protection Class	IP23
	Insulation Class	H
	Altitude	$\leq 1000\text{m}$
	Voltage Regulation, Steady State	$\leq \pm 1\%$
	Telephone Influence Factor	< 50
	Sudden Voltage Warp (100% Sudden Reduce)	$\leq \pm 1\%$
	Sudden Voltage Warp (Sudden Increase)	$\leq \pm 25\%$
	Voltage Stable Time (100% Sudden Reduce)	$\leq 6\text{S}$
	Voltage Stable Time (Sudden Increase)	$\leq 6\text{S}$
	Frequency Reduce	0-5% adjustable
	Frequency Regulation, Stead State	$\leq 1.5\%$
	Frequency Waving	$\leq 0.8\%$
	Sudden Frequency Warp (100% Sudden Reduce)	$\leq +12\%$
	Sudden Frequency Warp (100% Sudden Increase)	$\leq -10\%$
	Frequency Recovery Time (100% Sudden Reduce)	$\leq 5\text{S}$
	Frequency Recovery Time (Sudden Increase)	$\leq 5\text{S}$
Compliance Stands	GB755,BS5000,VDE0530,NEMAMG1-22,IED34-1,CSA22.2 and AS1359	

Control Panel System



MONICAN CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown 4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

1. Emergency Stop Button 2. Voltmeter and Selector Switch
3. Ammeter and Selector Switch 4. Frequency Meter
5. Hour Running Meter 6. Alart Buzzer



SMARTGEN CONTROL MODEL/ MANUAL OR ATSUSE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

Digital type, all function showed by LED



DEEPSEA CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop
6. With Remote Teleport Communication RS 485

Parameters of Operation:

Digital type, all function showed by LED