

Standard Features

MODEL	MT-P200
Standby Power(60Hz)	176KW/220KVA
Prime Power(60Hz)	160KW/200KVA
Engine	PERKINS 1106C-E66TAG4
Alternator	STAMFORD UCI274F

- **Engine(PERKINS.UK 1106C-E66TAG4)**
- Radiator 40°C max, fans are driven by belt, with safety guard
- 24V charge alternator
- **Alternator(STAMFORD UCI274F),**
- single bearing alternator, Protection Class IP22, insulation class H/H
- Dry Type air filter, fuel filter, oil filter, re-filter, absorber
- Main line circuit breaker
- Standard control panel
- Two 12V batteries, rack and cable
- Ripple flex exhaust pipe, Exhaust siphon, flange, muffler
- Operation manual



Generator Set Ratings						
Voltage	Frequency	Phase	P.F (COS ϕ)	Standby Amps	Standby Ratings (KW/KVA)	Prime Ratings (KW/KVA)
480/277	60	3	0.8	265	176/220	160/200
460/266	60	3	0.8	276	176/220	160/200
440/254	60	3	0.8	289	176/220	160/200
416/240	60	3	0.8	306	176/220	160/200

Prime Power (PRP): Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97(eqvISO8528); A10% overload capability is available for a period of 1 hour within a 12-hour period of operation.

Standby Power Rating (ESP): The standby power rating is applicable for supplying emergency

Dimension Of Generator Set	
Dimension(L*W*H)/CM For Open Type	240×98×160 CM
Net Weight/KG For Open Type	1500KG
Dimension(L*W*H)/CM For Sound Proof Type	340×135×195 CM
Net Weight/KG For Sound Proof Type	2200KG
Dimension (L*W*H)/MM For Trailer Type	
Net Weight/KG For Trailer Type	

Specification Of Engine		
Engine	Engine Model	1106C-E66TAG4
	Manufacturer	PERKINS UK
	Emissions statement	EU2007(EU97/68/EC Stage II)
	Prime Power	177.3KW/237.5HP
	Standby Power	196.3KW/263HP
	Engine Configuration	6Cylinder In Line, 4Stroke,Direct Injection
	Gas Feeding Model	Turbocharged
	Bore × Stroke	105 × 127 (MM)
	Displacement	6.6L
	Rated Speed	1800RPM
	Speed Governor	Electrical
	Starter Model	12V DC Start
	Fuel Consumption Prime Power (100% load)	48L/H
	Totally lubrication system Capacity	16.5L
	Coolant capacity	21.0L
	Cooling System	Water Cool
	Compression Ratio	16.2:1

Specification Of Alternator		
Alternator	Alternator Model	UCI274F
	Manufacturer	STAMFORD company
	Prime Output	165KW/206KVA
	Standby Output	181KW/227KVA
	Excitation Model	Brushless, Self-Exciting
	Cooling Method	Air Cooling
	Connection Type	3 Phase and 12 Wires "Star" Connection
	Power Factor	0.8
	Protection Class	IP22
	Insulation Class	H
	Altitude	$\leq 1000\text{m}$
	Voltage Regulation, Steady State	$\leq \pm 1\%$
	Telephone Influence Factor	< 50
	Sudden Voltage Warp (100% Sudden Reduce)	$\leq \pm 1\%$
	Sudden Voltage Warp (Sudden Increase)	$\leq \pm 25\%$
	Voltage Stable Time (100% Sudden Reduce)	$\leq 6\text{S}$
	Voltage Stable Time (Sudden Increase)	$\leq 6\text{S}$
	Frequency Reduce	0-5% adjustable
	Frequency Regulation, Stead State	$\leq 1.5\%$
	Frequency Waving	$\leq 0.8\%$
	Sudden Frequency Warp (100% Sudden Reduce)	$\leq +12\%$
	Sudden Frequency Warp (100% Sudden Increase)	$\leq -10\%$
	Frequency Recovery Time (100% Sudden Reduce)	$\leq 5\text{S}$
	Frequency Recovery Time (Sudden Increase)	$\leq 5\text{S}$
Compliance Stands	GB755,BS5000,VDE0530,NEMAMG1-22,IED34-1,CSA22.2 and AS1359	

Control Panel System



MONICAN CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown 4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

1. Emergency Stop Button 2. Voltmeter and Selector Switch
3. Ammeter and Selector Switch 4. Frequency Meter
5. Hour Running Meter 6. Alart Buzzer



SMARTGEN CONTROL MODEL/ MANUAL OR ATSUSE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

Digital type, all function showed by LED



DEEPSEA CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop
6. With Remote Teleport Communication RS 485

Parameters of Operation:

Digital type, all function showed by LED